

B100PROX-EH-SA

STANDALONE BIOMETRIC READER
WITH RFID CARD READER

B100PROX-EH-SA is a simple one-door standalone biometric and RFID system (or 2 doors when used with DINRTT or RU2). The reader programming is quick and easy. It can store up to 98 fingerprints and 2000 RFID cards. It has one integrated relay output and one exit button input.

If secure installation is needed, the reader can be connected to a remote relay unit in a secured area.

Complete setup and programming can be done by swiping the finger on the sensor.

It can read EM or HID compatible cards.



bx Black Edition
Product available in Black ABS

FEATURES


- Power supply: 9-14V CC, 150mA
- Capacity: 98 Fingerprints and 2000 Cards
- Output: One relay NO/NC contacts
- Output maximum current: 2A, 24V AC/DC
- Push button input: Yes
- Door time: Pulse (1-30 s) or Toggle(ON/OFF)
- Entry mode: Finger or Card
- Sensor: Swipe capacitive
- Card reader mode: EM4100 or HID compatible
- Read range: 2-5 cm
- Programming: By Master finger
- Admin/Installer fingers: 1 Admin and 1 Installer finger
- Backlight ON/OFF: Yes
- Buzzer ON/OFF: Yes
- Indication: Tricolor status LED
- Mounting: Surface mount
- IP factor: IP54 (internal use only)
- Operating temperature: 0°C to +50°C, non condensing

Compatible devices: RTT, DINRTT, RU2

VERSIONS




B100PROXS-EH-SA
Silver - Metal



B100PROXBK-EH-SA
Black - ABS

DIMENSIONS




FOBS & CARDS


EM
Fobs & Cards




Ref.	PBX-1E	PBX-1C	PBX-2	PBX-2C
Features	ABS Keyfob EM4100	Leather Keyfob EM4100	0.75mm ISO Card - EM4100	2mm NISO Card - EM4100



Access Granted



Idle Mode



Access Denied

Tricolor Indication uni-LED

WITH REMOTE RELAY AT SECURED AREA

