



**8461V**

## QUADRA + HANDSFREE MINI 1-FMLY KIT, SIMPLEBUS SYS.



SB2

2-wire Simplebus door entry monitor kit comprised of: 1 Quadra series wall-mounted external unit art. 4893M, 1 power supply unit art. 1209, 1 Handsfree Mini series colour monitor art. 6721W, 1 distribution terminal art. 1214/2C and 1 line closure terminal art. 1216.

## AWARDS

DESIGN  
MILANO



DESIGN PLUS  
powered by building



## 8461V

# QUADRA + HANDSFREE MINI 1-FMLY KIT, SIMPLEBUS SYS.

### KIT PRODUCT



#### 6721W

##### MINI HANDSFREE MONITOR, S2

Wall-mounted hands-free monitor with full-duplex audio and 4.3" / 16:9 colour screen. Allows brightness control, plus adjustment of the ringtone volume, which can be customised by choosing one of several different melodies. Equipped as standard with 5 sensitive touch back-lit controls for audio activation, door-opening, self-ignition, switchboard call, privacy service and LED signalling for the door status. Manages floor door calls as standard. Option of adding 3 additional buttons with accessory Art. 6734W. Complete with 2 x 8-position DIP-SWITCH for user code programming and button programming. The wall-mounting or residential series box backplate and riser distribution terminal Art. 1214/2C are included. The monitor can only be used in 2-wire Simplebus2 systems. Dimensions: 115x160x22mm.

### GENERAL DATA - 6721W

Product height (inch):	6.3
Product width (inch):	4.53
Product depth (inch):	0.87
Product weight (oz):	1.1
Product color:	White RAL9003
Material:	ABS
Wall mounting:	Yes
Desk base-mounted:	Yes, with a dedicated accessory



#### 4893M

##### QUADRA ENTRANCE PANEL W/ BUTTONS. 2 WIRES

Quadra series wall-mounted external video entry unit with mechanical buttons. Die-cast aluminium faceplate, wide-angle colour camera and a single LED for nighttime lighting. Indicator LED for call sent, lock-release activated, audio activated and system busy. Adjustment of speaker volume and audio balance. Power supply from bus line. External unit dimensions: 3.74"x7.68"x1.1".

### MAIN FEATURES - 4893M

Type:	Monoblock
Type of finish:	Die-cast aluminum
Audio/video system:	Yes
Wall-mounted:	Yes
Type of sensor:	1/4" CMOS
Lens size (inch):	0.08
Diagonal viewing angle (°):	100
Minimum color lighting (lux):	0.1
Horizontal resolution (TVL):	550
Signal/noise ratio (dB):	48
Maximum current absorption (mA):	250
Clamps:	LL RTE COM DO SE- SE+C NC NO

The technical specifications are subject to variations without warning.



## 8461V

# QUADRA + HANDSFREE MINI 1-FMLY KIT, SIMPLEBUS SYS.

### MAIN FEATURES - 4893M

Buttons to call:	Yes
Total buttons:	4
Microphone volume control:	Yes
Loudspeaker volume control:	Yes
Operating temperature (°F):	-13 ÷ 131
RH operating humidity (%):	25 ÷ 75
IP protection rating (IP code):	IP54
Vandal Resistant rating (IK code):	IK08
Backlighting color:	White



## 1216

### LINE TERMINATION TERMINAL

Line termination terminal. Provided as standard with mixer art.4888CU. To be mounted at the end of the riser, according to the indications given in the technical documentation, to optimise distribution of the signals.



## 1209

### 2-WIRE VIDEO KIT POWER SUPPLY UNIT

33 VDC power supply unit with overload and short circuit protection devices. It has two separate continuous outputs: one for external unit and one for the monitor power supply. Input voltage 110-240 VAC. Dimensions: 4.17"x2.44"x3.5" (6 DIN modules).

### MAIN FEATURES - 1209


Supply voltage (VAC):	110÷240
Input connector:	Terminal block
Applicable to DIN rail:	Yes
Number of DIN modules:	6
Max. current delivered (A):	1.2



**8461V**

## QUADRA + HANDSFREE MINI 1-FMLY KIT, SIMPLEBUS SYS.

### ACCESSORIES



**4791**

Adapter plate for Quadra

Plate allowing installation of the Quadra external unit in 1- and 2-module flush-mounted boxes by Comelit, Bticino and Urmet. Dimensions 137x236 mm



**4792**

RAIN SHIELD FOR QUADRA ENTRANCE PANEL

Rain shield in painted aluminum for Quadra entrance panel, gray colour. Dimensions (W x H x D): 3.9" x 8.27" x 1.61".



**4793MB**

BLACK FACEPLATE FOR QUADRA W/BUTTONS

Black faceplate for Quadra entrance panel with mechanical buttons



**4793MC**

CORTEN FACEPLATE FOR QUADRA W/BUTTONS

Corten colour faceplate for Quadra entrance panel with mechanical buttons



**4793MA**

ALUMINIUM FACEPLATE FOR QUADRA W/BUTTONS

Aluminium colour faceplate for Quadra entrance panel with mechanical buttons



**1217**

NAME TAG SHEETS FOR QUADRA ENTRANCE PANEL

The kit contains 10 sheets of adhesive labels for nameplates



**8461V**

## QUADRA + HANDSFREE MINI 1-FMLY KIT, SIMPLEBUS SYS.

### ACCESSORIES



**1235A**

#### NAMEPLATE LABEL PRINTING SOFTWARE


Dedicated software for the creation and printing of nameplate and information labels for Ikall, Vandalcom, Quadra and 316 Analog entrance panels. Requires use of adhesive labels art.1217, 1218, 1219 or art.1220. This software is available to download free of charge from the Comelit website



**6710**

#### BACKPLATE AND DISTRIBUTION TERMINAL FOR MINI MONITOR

Wall-mounting or residential series box backplate for MINI monitor, /BM versions with handset featuring magnetic induction for hearing aid wearers. Also includes riser distribution terminal Art. 1214/2C. Dimensions 145x100x4 mm.



**6733W**

#### ADDITIONAL BUTTONS KIT FOR MINI MONITOR, WHITE

Accessory for transforming MINI monitors Art 6700W-/BM and 6701W-/BM into versions with 8 buttons. Includes an 8-button faceplate and an electronic module for activating the buttons, which can be installed quickly without opening up the monitor.



**6720**

#### Access. cables external passage for MINI HF. S2

Wall support bracket for handsfree Mini monitor allowing thru-routing of external cables.



**6732**

#### DESK BASE FOR HANDSFREE MINI MONITOR

Desk base for desktop conversion of Handsfree Mini monitor. Complete with 1x 2 metre cable with RJ45 connector to connect monitor terminals to the coupler or domestic series socket. Dimensions: 140x190x140mm.



**1209**

#### 2-WIRE VIDEO KIT POWER SUPPLY UNIT

33 VDC power supply unit with overload and short circuit protection devices. It has two separate continuous outputs: one for external unit and one for the monitor power supply. Input voltage 110-240 VAC. Dimensions: 4.17"x2.44"x3.5" (6 DIN modules).



**8461V**

## QUADRA + HANDSFREE MINI 1-FMLY KIT, SIMPLEBUS SYS.

### ACCESSORIES



**1229A**

#### ADDITIONAL RINGTONE ACCESSORY. S2

Wall-mounted accessory for additional ringtone for direct connection to 2-wire bus. Allows ringtone selection and adjustment of ringtone volume with privacy function, equipped with dip switches for user code programming, floor door call input terminals and call repeat. Fitted with distribution terminal art. 1214/2C. Dimensions: 125x95x24mm.



**1256**

#### ACTUATOR RELAY

Intelligent Simplebus device for controlling a 10 A (12-24 V relay contact) on board. It can be used in Simplebus 1 and Simplebus 2 systems. Depending on the position of the jumper, the device provides six distinct functions: call repetition, activation on porter switchboard call pushbutton, door opening (without external unit), activation on actuator pushbutton, activation on actuator pushbutton with code. For use and programming of the function required, follow the indications given in the technical documentation. If used in mixed audio/video systems, the actuator relay needs terminal art. 1214/2 to be purchased separately. Power supply: 12V AC or 20V DC. Dimensions: 2.6"x3.3"x1.4". (4 DIN modules).



**1404**

#### DIGITAL SWITCHING DEVICE. 2-WIRE SYSTEM

Audio/video switching module for Simplebus 2 2-wire digital systems. To be used in systems with more than one entrance. Power supply from bus line. Dimensions: 60x85x35 mm (4 DIN modules).



**1405**

#### DIGITAL EXCHANGE 2 QUADRA INPUTS. S2

Audio/video switching module for audio/video kit systems. For use in systems with a maximum of 2 entrances with Quadra series external unit. Power supply from bus line. Dimensions: 35x90x58mm (2 DIN modules).



**1409**

#### ACCESSORY FOR REMOTE COLOUR CAMERAS, 2-WIRE SYSTEM

Remote camera module for Simplebus 2 2-wire digital systems. Allows management of up to 3 colour cameras in cyclical sequence from door entry monitors using a dedicated button. 12 Vac or 20 Vdc power supply. Dimensions: 60x85x35 mm (4 DIN modules).