



8461X

QUADRA + MAXI SINGLE-FAMILY KIT, SIMPLEBUS SYSTEM



Simplebus Top 2-wires kit comprised of: - no. 1 Quadra series wall-mounted external unit art. 4893M - no. 1 Maxi series hands-free colour monitor art. 6801W - no. 1 power supply unit art. 1209 - no. 1 flush-mounted box art. 6817 - no. 1 wall bracket art. 6820 - no. 1 line closure terminal art. 1216

AWARDS





8461X

QUADRA + MAXI SINGLE-FAMILY KIT, SIMPLEBUS SYSTEM

KIT PRODUCT



4893M

QUADRA ENTRANCE PANEL W/ BUTTONS. 2 WIRES

Quadra series wall-mounted external video entry unit with mechanical buttons. Die-cast aluminium faceplate, wide-angle colour camera and a single LED for nighttime lighting. Indicator LED for call sent, lock-release activated, audio activated and system busy. Adjustment of speaker volume and audio balance. Power supply from bus line. External unit dimensions: 95x195x28 mm.

MAIN FEATURES - 4893M

Type:	Monoblock entrance panel
Material:	Die-cast aluminium
Audio/video system:	Yes
Wall-mounted:	Yes
Camera:	Colors
Type of sensor:	1/4" CMOS
Lens size (inch):	0.08
Diagonal viewing angle (°):	100
Minimum colour lighting (lux):	1
Power supply:	Bus
Maximum current absorption (mA):	250
Clamps:	LL RTE COM DO SE- SE+C NC NO
Buttons to call:	Yes
Total buttons:	4
Microphone volume control:	Yes
Loudspeaker volume control:	Yes
Operating temperature (°F):	-13 ÷ 131
IP protection rating:	IP54
Vandal Resistant rating (IK code):	IK08
Backlighting colour:	White

6801W

7-INCH MAXI MONITOR, SBTOP



Colour monitor for flush-mounting (on Art. 6817) or wall-mounting (on support Art. 6820) with 7" 16:9 screen, hands-free full-duplex audio and touch sensitive controls. Allows brightness, contrast and audio volume control, plus adjustment of the volume of the ringtone, which can be customised with a choice of different melodies. Equipped as standard with control buttons for lock-release and audio enable/disable with relative indicator LEDs, plus 6 further buttons for self-ignition, privacy service and other programmable functions. Manages floor door calls and call repeat as standard. Complete with 2 x 8-position DIP-switches for user code programming and button programming. Equipped with riser distribution terminal Art 1214/2C. The monitor can only be used in 2-wire SimplebusTop Color systems. Dimensions: 223x124x25mm.



8461X

QUADRA + MAXI SINGLE-FAMILY KIT, SIMPLEBUS SYSTEM

MAIN FEATURES - 6801W

Audio system:	No
Audio/video system:	Yes
Flush-mounted:	Yes
Wall-mounted:	Yes
Desk base-mounted:	Yes
Hands-free function:	Yes
Induction loop function:	No
Type of display:	LCD
Display size (inch):	7" 16:9
Touch screen display:	No
Display resolution HxV (inch):	800x480
B/W or colour display:	Color
Product colour:	White RAL9003
Sensitive Touch technology:	Yes
Total buttons:	14
LED signaling (no.):	14
Wi-Fi Port:	No
Comaptibility with Video Entry Comelit App:	No



1209

2-WIRE VIDEO KIT POWER SUPPLY UNIT

33 VDC power supply unit with overload and short circuit protection devices. It has two separate continuous outputs: one for external unit and one for the monitor power supply. Input voltage 110-240 VAC. Dimensions: 106 x 62 x 89 mm (6 DIN modules).

MAIN FEATURES - 1209

Alternating input voltage (VAC):	110÷240
Output voltage (VDC):	33
Input connector:	Terminal block
Applicable to DIN rail:	Yes
Number of DIN modules:	6
Max. current delivered (A):	1.20



8461X

QUADRA + MAXI SINGLE-FAMILY KIT, SIMPLEBUS SYSTEM

KIT PRODUCT



6817

FLUSH-MOUNTED BOX FOR MAXI MONITOR

Flush-mounted box in black ABS. Dimensions: 212x115x50mm



6820

SBC & VIP MAXI MONITOR WALL SUPPORT

Wall support for Maxi monitor. White. Dimensions: 216x117x16 mm.



1216

VIDEO RISER TERMINATION FOR SIMPLEBUS


Line termination terminal. To be mounted at the end of the riser, according to the indications given in the technical documentation, to optimise distribution of the signals.



8461X

QUADRA + MAXI SINGLE-FAMILY KIT, SIMPLEBUS SYSTEM


ACCESSORIES



4791

Adapter plate for Quadra

Plate allowing installation of the Quadra external unit in 1- and 2-module flush-mounted boxes by Comelit, Bticino and Urmet. Dimensions 137x236 mm



4792

RAIN SHIELD FOR QUADRA ENTRANCE PANEL

Rain shield in painted aluminum for Quadra entrance panel, grey colour. Dimensions (W x H x D): 99 x 210 x 41 mm.



4793MB

BLACK FACEPLATE FOR QUADRA W/BUTTONS



4793MC


CORTEN FACEPLATE FOR QUADRA W/BUTTONS

Corten color faceplate for Quadra entrance panel with mechanical buttons.



4793MA

ALUMINIUM FACEPLATE FOR QUADRA W/BUTTONS



1217

NAME TAG SHEETS FOR QUADRA ENTRANCE PANEL

The kit contains 10 sheets of adhesive labels for nameplates



8461X

QUADRA + MAXI SINGLE-FAMILY KIT, SIMPLEBUS SYSTEM

ACCESSORIES



1235A

NAMEPLATE LABEL PRINTING SOFTWARE

Dedicated software for the creation and printing of nameplate and information labels for Ikall, Vandalcom, Quadra and 316 Analog entrance panels. Requires use of adhesive labels art.1217, 1218, 1219 or art.1220. This software is available to download free of charge from the Comelit website



6817

FLUSH-MOUNTED BOX FOR MAXI MONITOR

Flush-mounted box in black ABS. Dimensions: 212x115x50mm



6820

SBC & VIP MAXI MONITOR WALL SUPPORT

Wall support for Maxi monitor. White. Dimensions: 216x117x16 mm.



6812

DESK BASE FOR MAXI MONITOR

Desk base for desktop conversion of Maxi monitor. Dimensions: 105x75x110 mm.



1209

2-WIRE VIDEO KIT POWER SUPPLY UNIT

33 VDC power supply unit with overload and short circuit protection devices. It has two separate continuous outputs: one for external unit and one for the monitor power supply. Input voltage 110-240 VAC. Dimensions: 106 x 62 x 89 mm (6 DIN modules).



1229A

ADDITIONAL RINGTONE ACCESSORY FOR SIMPLEBUS2 SYSTEM

Wall-mounted accessory for additional ringtone for direct connection to 2-wire bus. Allows ringtone selection and adjustment of ringtone volume with privacy function, equipped with dip switches for user code programming, floor door call input terminals and call repeat. Fitted with distribution terminal art. 1214/2C. Dimensions: 125x95x24 mm.



8461X

QUADRA + MAXI SINGLE-FAMILY KIT, SIMPLEBUS SYSTEM


ACCESSORIES



1256

ACTUATOR RELAY

Intelligent Simplebus device for controlling a 12-24 V relay contact. If used in mixed audio/video systems, the actuator relay needs a video filter to be purchased separately. Power supply: 12V AC or 20V DC. Dimensions: 66x85x35 mm (4 DIN modules).



1404

DIGITAL SWITCHING DEVICE. 2-WIRE SYSTEM

Audio/video switching module for Simplebus Top 2-wire digital systems. To be used in systems with more than one entrance. Power supply from bus line. Dimensions: 60x85x35 mm (4 DIN modules).



1405

DIGITAL EXCHANGE 2 QUADRA INPUTS. SBTOP

Audio/video switching module for audio/video kit systems. For use in systems with a maximum of 2 entrances with Quadra series external unit. Power supply from bus line. Dimensions: 35x90x58mm (2 DIN modules).



1409

ACCESSORY FOR REMOTE COLOUR CAMERAS, 2-WIRE SYSTEM

Remote camera module for Simplebus Top 2-wire digital systems. Allows management of up to 3 colour cameras in cyclical sequence from door entry monitors using a dedicated button. 12 Vac or 20 Vdc power supply. Dimensions: 60x85x35 mm (4 DIN modules).